2. Electrical Parts List

Location no	Code no.	Description; Specification	Remarks
		****** MCD-CF300 Parts List ******	
	AH30-00066B	PHONE-EAR;Gray/Silver,EP-50G,16ohm,990mm	
	AH59-00977J	REMOCON-ASSY;RM-CF300,SAMSUNG,-, ,-,-,-,	
CD DECK	AH59-01260A	DECK;DA50A,MCD-CM300,BALL,-,-,-,DEC	
	AH92-01963C	**ASSY PCB-MAIN;MCD-CF300,ASS'Y MAIN**	
MSW2	3409-001081	SWITCH-DETECTOR;12V DC,0.1A,SPST,30gf,PU	
CN301	3711-004381	CONNECTOR-HEADER;BOX,6P,1R,1.5MM,STRAIGH	
JA601	3722-002127	JACK-DC POWER;3P,1.65PI/4.4PI,SN,WHT	
JA501	AH37-00015A	3897255ONE;-,-,-,-,MY-MP200	
PACK1	AH40-00015M	TUNER-PACK;DA-104,MCD-CM300,FM,-,225Khz,	
	AH94-01297C	ASSY CHIP-MAIN,MCD-CF300;MCD-CF300,MAIN	
D201	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
D202	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
D603	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
D601	0403-001306	DIODE-ZENER;MMGDZ3.0B,3.01-3.22V,500MW,L	
D401	0404-000144	DIODE-SCHOTTKY;SB01-05CP,50V,100MA,SOT-2	
D602	0404-000144	DIODE-SCHOTTKY;SB01-05CP,50V,100MA,SOT-2	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q509	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q510	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q601	0501-000528	TR-SMALL SIGNAL;KSC2982B,NPN,500mW,SOT-8	
Q602	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2	
Q506	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q504	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q502	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q402	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q103	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q505	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q305	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q303	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q301	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q306	0504-000158	TR-DIGITAL;KSR2104,PNP,200mW,47K/47K,SOT	
Q304	0504-000158	TR-DIGITAL;KSR2104,PNP,200mW,47K/47K,SOT	
Q302	0504-000158	TR-DIGITAL;KSR2104,PNP,200mW,47K/47K,SOT	
Q604	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q603	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q503	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q102	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q401	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q501	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
IC301	0903-001334	IC-MICROCONTROLLER;S3F84BBXZZ-TWRB,8BIT,	
IC204	0904-001841	IC-DSP;S5L9234X01,-,LQFP,64P,10.0X10.	
IC401	1003-001678	IC-MOTOR DRIVER;FAN8048,LQFP,48P,70X70MM	
IC202	1105-001261	IC-DRAM;12L1616A,16BIT,TSOP,50P,400MIL	
IC203	1107-001361	IC-FLASH MEMORY;SST39VF040,512K##8BIT,TS	
IC502	1201-002039	IC-POWER AMP;TA2152FN,SSOP,24P,7.8X5.6MM	
IC101	1201-002096	IC-RF AMP;S1L9227X,LQFP,48P,7X7MM,-,-,PL	
IC303	1203-002564	IC-VOL. DETECTOR;XC61CC2502MR,SOT-23,3P,	
IC601	1203-003187	IC-DC/DC CONVERTER;XC6383A,SOT-89,3P,4.5	
IC201	1204-002243	IC-DECODER;S5L9278X,TQFP,100P,14.0*14.0M	
IC501	1204-002290	IC-VOLUME/TONE CONT.;E-TDA7463AD,SSOP,20	
R525	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
R315	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R313	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R132	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R501	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R354	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R341	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R305	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R304	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R235	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R236	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R237	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R238	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R234	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R233	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R232	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R231	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R230	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R529	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R527	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R505	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R504	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R408	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R242	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R241	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R240	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R239	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R216	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R215	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R213	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R212	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R211	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R131	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R105	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R104	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R103	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R228	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R227	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R226	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R225	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R224	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R217	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R219	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R220	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R221	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R229	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R210	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R351	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R523	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R524	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R605	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R350	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R108	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R109	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R123	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R208	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R333	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R335	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R518	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
R517	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
R336	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R521	2007-000086	R-CHIP;5.6Kohm,5%,1/10W,TP,1608	
R522	2007-000086	R-CHIP;5.6Kohm,5%,1/10W,TP,1608	
R404	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R405	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R506	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R507	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R570	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R571	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R403	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R106	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R107	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R342	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R343	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R344	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R531	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R530	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R520	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R519	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R406	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R337	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R330	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R329	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R328	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R327	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R326	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R361	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R360	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R353	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R347	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R346	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R345	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R319	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R311	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R310	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R309	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R308	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R301	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R325	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R324	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R323	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R320	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R321	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R322	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R515	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R514	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R120	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R117	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R118	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R119	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R340	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R348	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R401	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R402	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R508	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R601	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R214	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	

Location no	Code no.	Description; Specification	Remarks
R303	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R306	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R307	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R318	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R339	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R122	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	
R121	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	
R302	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R209	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R116	2007-000115	R-CHIP;82ohm,5%,1/10W,TP,1608	
R332	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R352	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R334	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R115	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
R608	2007-000310	R-CHIP;10OHM,5%,1/2W,DA,TP,5025	
R603	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R602	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R101	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R609	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R528	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R526	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R407	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R130	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R516	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	
R578	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	
C104	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	
C127	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C268	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C269	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C270	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C271	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C272	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C125	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C261	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C265	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C266	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C267	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C315	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C119	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C131	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C121	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C123	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
C210	2203-000646	C-CER,CHIP;0.024NF,5%,50V,C0G,TP,1608	
C209	2203-000646	C-CER,CHIP;0.024NF,5%,50V,C0G,TP,1608	
C228	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C103	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C102	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C118	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C122	2203-001408	C-CER,CHIP;0.27nF,5%,50V,NP0,TP,1608	
C215	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C214	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C213	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C114	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C113	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C112	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C571	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,TP,1608	
C570	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,TP,1608	
C403	2203-001640	C-CER,CHIP;0.39nF,10%,50V,X7R,TP,1608	
C523	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C522	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C406	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C405	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C302	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C254	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C252	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C305	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C308	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C309	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C311	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C244	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C245	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C246	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C247	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C249	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C250	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C251	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C313	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C514	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C527	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C572	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C576	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C601	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C605	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C608	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C404	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C408	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C410	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C412	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C414	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C415	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C506	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C132	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	

Location no	Code no.	Description; Specification	Remarks
C202	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C203	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C206	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C207	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C211	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C212	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C106	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C108	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C111	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C115	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C117	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C124	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C130	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C216	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C234	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C235	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C236	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C237	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C238	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C241	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C243	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C218	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C221	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C223	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C227	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C233	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C231	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C230	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C532	2203-005005	C-CER,CHIP;100nF,+80-20%,16V,Y5V,-,1608	
C533	2203-005005	C-CER,CHIP;100nF,+80-20%,16V,Y5V,-,1608	
C574	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C575	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C603	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C525	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C105	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C126	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C314	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C402	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C524	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C413	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C512	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C513	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C604	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C606	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C220	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C301	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C407	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C409	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C411	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C602	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.	
C520	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C521	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C529	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C530	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C224	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C225	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C517	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C518	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C515	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C505	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C310	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C307	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C248	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C580	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C579	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C578	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C577	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C526	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C240	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C205	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C204	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C201	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C133	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C116	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C232	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C229	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C222	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C219	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C217	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C128	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C107	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C312	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C401	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C528	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C607	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C226	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C109	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C110	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C129	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C208	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
L503	2703-000002	INDUCTOR-SMD;100uH,10%,3225	
L405	2703-000002	INDUCTOR-SMD;100uH,10%,3225	
L406	2703-000398	INDUCTOR-SMD;10uH,10%,3225	

Location no	Code no.	Description; Specification	Remarks
L404	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L403	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L302	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L301	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L601	2703-001070	INDUCTOR-SMD;100uH,10%,4532	
L402	2703-001194	INDUCTOR-SMD;100uH,20%,7070	
L401	2703-001194	INDUCTOR-SMD;100uH,20%,7070	
X201	2802-001209	RESONATOR-CERAMIC;16.934MHZ,0.5%,TP,3.2X	
X301	2802-001211	RESONATOR-CERAMIC;8MHZ,0.1%,TP,3.7X3.1X1	
L506	3301-000325	BEAD-SMD;60ohm,3.2x2.5x1.3mm,400mA,TP,,	
BD602	3301-000325	BEAD-SMD;60ohm,3.2x2.5x1.3mm,400mA,TP,,	
BD504	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
BD503	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
BD502	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
BD501	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
MSW7	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW8	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW9	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW6	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW5	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW10	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW1	3408-001038	SWITCH-SLIDE;4V,300mA,SPST,ON-ON,-	
CN101	3708-001022	CONNECTOR-FPC/FFC/PIC;18P,0.5MM,SMD-A,SN	
CN102	3708-001022	CONNECTOR-FPC/FFC/PIC;18P,0.5MM,SMD-A,SN	
CN302	3711-005161	CONNECTOR-HEADER;BOX,6P,1R,1MM,SMD-A,SN,	
	AH92-01964A	**ASSY PCB-FRONT;MCD-CM300,ASS'Y FRONT**	
FLCD	AH07-00102A	LCD-DISPLAY;PC267HGN01,MCD-HF200,FULL DO	
	AH41-00645A	FPC;MCD-CM300,MS0192-01,PCB,18P;-,	
	AH94-01298A	ASSY CHIP-FRONT,MCD-CM300;MCD-CM300,FRON	
FR17	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR16	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR15	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR14	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR18	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
FR2	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
FR9	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
FR12	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	
FR13	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	
FR1	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
FR3	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
FR11	2007-000497	R-CHIP;2.2Mohm,1%,1/10W,TP,1608	
FC5	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
FC10	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
FC4	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC3	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC2	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC14	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC1	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC8	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
FC7	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
FC6	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
FC9	2404-000148	C-TA,CHIP;1uF,10%,20V,-,TP,3216	
FSW4	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FSW3	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FSW2	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FSW1	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FCW1	3708-001022	CONNECTOR-FPC/FFC/PIC;18P,0.5MM,SMD-A,SN	

Location no	Code no.	Description; Specification	Remarks

****** MCD-CM300 Parts List ******

	AH30-00066B	PHONE-EAR;Gray/Silver,EP-50G,16ohm,990mm	
	AH59-00977H	REMOCON-ASSY;RM-CM300,SAMSUNG,-, ,-,-,-,	
CD DECK	AH59-01260A	DECK;DA50A,MCD-CM300,BALL,-,-,-,DEC	
	AH92-01963A	**ASSY PCB-MAIN;MCD-CM300,ASS'Y MAIN**	
MSW2	3409-001081	SWITCH-DETECTOR;12V DC,0.1A,SPST,30gf,PU	
CN301	3711-004381	CONNECTOR-HEADER;BOX,6P,1R,1.5MM,STRAIGH	
JA601	3722-002127	JACK-DC POWER;3P,1.65PI/4.4PI,SN,WHT	
JA501	AH37-00015A	3897255ONE;-,-,-,-,MY-MP200	
	AH94-01297A	ASSY CHIP-MAIN,MCD-CM300;MCD-CM300,MAIN	
D201	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
D202	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
D603	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323	
D601	0403-001306	DIODE-ZENER;MMGDZ3.0B,3.01-3.22V,500MW,L	
D401	0404-000144	DIODE-SCHOTTKY;SB01-05CP,50V,100MA,SOT-2	
D602	0404-000144	DIODE-SCHOTTKY;SB01-05CP,50V,100MA,SOT-2	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q601	0501-000528	TR-SMALL SIGNAL;KSC2982B,NPN,500mW,SOT-8	
Q602	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2	
Q504	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q402	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q103	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
Q305	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q303	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q301	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
Q306	0504-000158	TR-DIGITAL;KSR2104,PNP,200mW,47K/47K,SOT	
Q304	0504-000158	TR-DIGITAL;KSR2104,PNP,200mW,47K/47K,SOT	
Q302	0504-000158	TR-DIGITAL;KSR2104,PNP,200mW,47K/47K,SOT	
Q604	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q603	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q503	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q401	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
Q102	0505-001426	FET-SILICON;IRLML6401,P,-12V,-4.3A,0.05o	
IC301	0903-001334	IC-MICROCONTROLLER;S3F84BBXZZ-TWRB,8BIT,	
IC204	0904-001841	IC-DSP;S5L9234X01,-,LQFP,64P,10.0X10.	
IC401	1003-001678	IC-MOTOR DRIVER;FAN8048,LQFP,48P,70X70MM	
IC202	1105-001261	IC-DRAM;12L1616A,16BIT,TSOP,50P,400MIL	
IC203	1107-001361	IC-FLASH MEMORY;SST39VF040,512K##8BIT,TS	
IC502	1201-002039	IC-POWER AMP;TA2152FN,SSOP,24P,7.8X5.6MM	
IC101	1201-002096	IC-RF AMP;S1L9227X,LQFP,48P,7X7MM,-,-,PL	
IC303	1203-002564	IC-VOL. DETECTOR;XC61CC2502MR,SOT-23,3P,	
IC601	1203-003187	IC-DC/DC CONVERTER;XC6383A,SOT-89,3P,4.5	
IC201	1204-002243	IC-DECODER;S5L9278X,TQFP,100P,14.0*14.0M	
R132	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R501	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R354	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R341	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R305	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R304	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R233	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R234	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R235	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R236	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R232	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R231	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R230	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R228	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R527	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R408	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R242	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R241	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R240	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R239	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R238	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R237	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R227	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R215	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R213	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R212	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R211	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R131	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R105	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R104	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R103	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R226	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R225	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R224	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R221	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R216	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R217	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R219	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R220	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R229	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	

Location no	Code no.	Description; Specification	Remarks
R210	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R350	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R351	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R605	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R208	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R108	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R109	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R123	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R333	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R335	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R336	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R404	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R403	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R405	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R570	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R571	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R344	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R343	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R342	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R107	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R106	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R101	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R406	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R330	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R329	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R328	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R327	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R326	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R360	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R353	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R346	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R345	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R337	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R311	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R310	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R309	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R308	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R301	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R325	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R324	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R323	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R322	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R321	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R120	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R119	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R118	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R117	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R348	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R340	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R339	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R401	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R402	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R601	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R214	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R303	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R306	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R318	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R312	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R307	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R121	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	
R122	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	
R302	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R209	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R116	2007-000115	R-CHIP;82ohm,5%,1/10W,TP,1608	
R332	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R334	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R352	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R575	2007-000130	R-CHIP;39Kohm,5%,1/10W,TP,1608	
R574	2007-000130	R-CHIP;39Kohm,5%,1/10W,TP,1608	
R115	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
R608	2007-000310	R-CHIP;10OHM,5%,1/2W,DA,TP,5025	
R603	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R602	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R609	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R526	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R407	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R130	2007-000637	R-CHIP;270Kohm,5%,1/10W,TP,1608	
R578	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	
C104	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	
C127	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C268	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C269	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C270	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C271	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C272	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C125	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C261	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C265	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C266	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C267	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C315	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	

Location no	Code no.	Description; Specification	Remarks
C119	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C131	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C121	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C123	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
C209	2203-000646	C-CER,CHIP;0.024NF,5%,50V,C0G,TP,1608	
C210	2203-000646	C-CER,CHIP;0.024NF,5%,50V,C0G,TP,1608	
C228	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C102	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C103	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C118	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C122	2203-001408	C-CER,CHIP;0.27nF,5%,50V,NP0,TP,1608	
C215	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C214	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C213	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C114	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C113	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C112	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C571	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,TP,1608	
C570	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,TP,1608	
C403	2203-001640	C-CER,CHIP;0.39nF,10%,50V,X7R,TP,1608	
C406	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C405	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C251	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C252	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C254	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C302	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C305	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C308	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C250	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C243	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C244	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C245	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C246	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C247	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C249	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C309	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C415	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C572	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C576	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C601	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C605	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C608	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C414	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C311	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C313	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C404	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C408	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C410	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C412	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C241	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C132	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C202	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C203	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C206	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C207	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C211	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C130	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C106	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C108	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C111	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C115	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C117	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C124	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C212	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C233	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C234	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C235	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C236	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C237	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C238	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C231	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C216	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C218	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C221	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C230	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C227	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C223	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C533	2203-005005	C-CER,CHIP;100nF,+80-20%,16V,Y5V,-,1608	
C574	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C575	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C603	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C532	2203-005005	C-CER,CHIP;100nF,+80-20%,16V,Y5V,-,1608	
C105	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C126	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C314	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C402	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
C413	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C512	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C513	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C604	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C606	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C220	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	

Location no	Code no.	Description; Specification	Remarks
C301	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C407	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C409	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C411	2402-001008	C-AL,SMD;220uF,20%,4V,GP,TP,6.6x6.6x5.4	
C602	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.	
C224	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C225	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
C307	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C248	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C240	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C232	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C310	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C577	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C578	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C579	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C580	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C116	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C133	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C201	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C204	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C205	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C229	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C222	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C219	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C217	2404-000471	C-TA,CHIP;22uF,20%,6.3V,GP,TP,3216,2.7	
C128	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C107	2404-001039	C-TA,CHIP;47uF,20%,6.3V,GP,TP,3528,-	
C226	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C312	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C401	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C607	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C109	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C110	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C129	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
C208	2404-001293	C-TA,CHIP;100UF,20%,6.3V,WT,TP,3528	
L405	2703-000002	INDUCTOR-SMD;100uH,10%,3225	
L406	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L404	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L403	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L302	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L301	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
L601	2703-001070	INDUCTOR-SMD;100uH,10%,4532	
L402	2703-001194	INDUCTOR-SMD;100uH,20%,7070	
L401	2703-001194	INDUCTOR-SMD;100uH,20%,7070	
X201	2802-001209	RESONATOR-CERAMIC;16.934MHZ,0.5%,TP,3.2X	
X301	2802-001211	RESONATOR-CERAMIC;8MHZ,0.1%,TP,3.7X3.1X1	
L506	3301-000325	BEAD-SMD;60ohm,3.2x2.5x1.3mm,400mA,TP,,	
BD602	3301-000325	BEAD-SMD;60ohm,3.2x2.5x1.3mm,400mA,TP,,	
BD504	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
BD503	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
BD502	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
BD501	3301-001643	BEAD-SMD;1500ohm,1608,50mA,TP,1200ohm/6	
MSW7	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW8	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW9	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW10	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW5	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW6	3404-001238	SWITCH-TACT;12V DC,50MA,160GF,3.5X7.8X3.	
MSW1	3408-001038	SWITCH-SLIDE;4V,300mA,SPST,ON-ON,-	
CN101	3708-001022	CONNECTOR-FPC/FFC/PIC;18P,0.5MM,SMD-A,SN	
CN102	3708-001022	CONNECTOR-FPC/FFC/PIC;18P,0.5MM,SMD-A,SN	
CN302	3711-005161	CONNECTOR-HEADER;BOX,6P,1R,1MM,SMD-A,SN,	
	AH92-01964A	**ASSY PCB-FRONT;MCD-CM300,ASS'Y FRONT**	
FLCD	AH07-00102A	LCD-DISPLAY;PC267HGN01,MCD-HF200,FULL DO	
	AH41-00645A	FPC;MCD-CM300,MS0192-01,PCB,18P-,	
	AH94-01298A	ASSY CHIP-FRONT,MCD-CM300;MCD-CM300,FRON	
FR17	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR16	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR15	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR14	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
FR18	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
FR2	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
FR9	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
FR12	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	
FR13	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	
FR1	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
FR3	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
FR11	2007-000497	R-CHIP;2.2Mohm,1%,1/10W,TP,1608	
FC5	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
FC10	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
FC4	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC3	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC2	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC14	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC1	2203-005819	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,-,1608	
FC8	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
FC7	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
FC6	2404-000139	C-TA,CHIP;10uF,20%,6.3V,-,TP,3216,-	
FC9	2404-000148	C-TA,CHIP;1uF,10%,20V,-,TP,3216	
FSW4	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FSW3	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FSW2	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FSW1	3404-001121	SWITCH-TACT;12V DC,50mA,160gf,4.8x4.8x0.	
FCW1	3708-001022	CONNECTOR-FPC/FFC/PIC;18P,0.5MM,SMD-A,SN	